

ZN3770B Artificial Power Network (LISN) - Product Datasheet

Manufacturer: Beijing Daze Technology Co., Ltd.



1. Product Overview

Model: ZN3770B
Type: Artificial Power Network (LISN)
Frequency Range: 150kHz – 30MHz

The ZN3770B is a V-type 50Ω/50μH Artificial Power Network (LISN), designed for conducted disturbance tests. It provides stable impedance within the specified frequency range and isolates the Device Under Test (DUT) from high-frequency noise on the power line, coupling interference voltage to the receiver. The device complies with the CISPR16-1 standard, equivalent to the national standard GB/T6113.1.

2. Technical Specifications

Parameter	Specification
Frequency Range	150kHz – 30MHz
Impedance Characteristics	50Ω/50μH
Impedance Error	±20% (Refer to Impedance Characteristics Chart)
Phase Angle Error	±11.5°
Isolation	≥40dB
Voltage Divider Ratio	Refer to Divider Ratio Table
Operating Current	4×100A
Operating Voltage	AC 400V 50Hz; DC 600V
Auxiliary Power	AC 220V/0.5A
RF Output	BNC 50Ω
Dimensions	410mm × 240mm × 500mm
Weight	25kg

3. Key Features

- **Stable Impedance:** Provides stable impedance within the specified frequency range for conducted disturbance tests.
 - **High Isolation:** Effectively isolates high-frequency interference, ensuring separation of the DUT from noise on the power line.
 - **Compliance with Standards:** Meets the CISPR16-1 standard, equivalent to GB/T6113.1, for conducted disturbance tests.
-

4. Panel Functions

1. Front Panel

- Ground Terminal
- Selector Switch
- Measurement Output
- Power Output
- Calibration Ground Terminal

2. Rear Panel

- Power Input
 - Ground Terminal
 - Auxiliary Power Input
-

5. Operating Instructions

1. Three-Phase Four-Wire System

- Securely connect the PE terminal to the grounding plate (both front and rear grounding).
- Connect the front panel L1, L2, L3, N power output terminals to the DUT input terminals L1, L2, L3, N, and connect the interference test equipment (50Ω input).
- Connect the rear panel L1, L2, L3, N power input terminals to the mains L1, L2, L3, N, and then turn on the power.
- Use the selector switch to choose the desired test line.

2. Single-Phase System

- Securely connect the PE terminal to the grounding plate (both front and rear grounding).
- Connect the front panel L3, N terminals to the DUT input terminals L, N, and connect the interference test equipment (50Ω input).

- Connect the rear panel L3, N terminals to the mains L, N, and then turn on the power.
- Use the selector switch to select the L3, N line for testing.
- When the operating current exceeds 60A, use a fan for cooling (rear panel power socket requires 220V power).

6. Caution

- Only trained personnel are allowed to operate this device.
- Read the user manual carefully before use, and follow the connection instructions.
- The device should be used in a ventilated, dry environment, and the PE grounding must be securely connected. Safety warning signs must be displayed during operation.

7. Standard Accessories

Item	Quantity
ZN3770B Main Unit	1 unit
User Manual	1 copy
N-N Test Cable (1m)	1 unit
Power Cable	1 unit

8. Warranty

- **Warranty Period:** 18 months from the date of shipment, covering defects under normal usage and transportation conditions.

9. Product Photo



Contact Information:

Beijing Daze Technology Co., Ltd.

Phone: 010-64357789

Fax: 010-64373942

Website: www.zn734.com.cn

Email: 781920339@qq.com